

## 1/2 HP AC BELT DRIVE WIFI® Garage Door Opener DEPENDABLE PERFORMANCE



### KEY FEATURES

**QUIET OPERATION**  
Belt Drive

**WI-FI**  
Built In

### INCLUDED ACCESSORIES:

#### Multi-Function Control Panel

Includes lockout controls and accessory programmability.



6080979

882RGDW

#### 3-Button Remote Control

Operates up to 3 openers or MyQ Light Accessories.



2220178

893RCX

## RELIABLE

**1/2 HP AC MOTOR** IS PURPOSEFULLY DESIGNED AND BUILT TO LAST.

**BELT DRIVE SYSTEM** FOR QUIET, MAINTENANCE-FREE PERFORMANCE.

**WARRANTY** 4-YEAR MOTOR, 1-YEAR PARTS.

## SMART

**BUILT-IN WIFI** FOR THE EASIEST WAY TO CONNECT THE GARAGE.

**MYQ MOBILE APP** LETS USERS RECEIVE ALERTS AND CONTROL THE OPENER FROM ANYWHERE.

## SECURE

**SECURITY+ 2.0®** SENDS A NEW CODE WITH EVERY REMOTE CLICK.

**POSILOCK®** ELECTRONICALLY PROTECTS AGAINST FORCED OPENINGS.

**ALERT-2-CLOSE** SIGNALS WHEN A DOOR IS BEING CLOSED BY MyQ.

**THE PROTECTOR SYSTEM®** INVISIBLE LIGHT BEAM AUTO-REVERSES THE DOOR IF THERE IS AN OBSTRUCTION.

### POWERFUL ADD-ONS:

#### Mini Universal Remote Control

Compact and portable to provide quick, easy garage access..



2220185

374UT

#### Remote Light Control

Plug in any lamp to this device to control it with a smartphone or garage remote.



2220174

825LM

#### Remote Light Switch

Replaces an existing wall switch to control home lighting with a smartphone or garage remote.



2220183

823LM

#### Garage Door and Gate Monitor

Monitors and closes up to 4 garage doors from any room in the house.



2220175

829LM

## MASTERFUL ENGINEERING.

### MOTOR



- ½ Horsepower AC
- 1,625 RPM
- Automatic Thermal Protection
- Permanent Lubrication

### POWER



- 120V AC
- 60 Hz Voltage
- 6A Current Rating
- UL Listed
- 4' Power Cord (3-Prong)

### MECHANICS



- **Steel Chassis, T-Rail and Trolley**
- **Full Reinforced Belt Drive Mechanism** (16:1 Gear Reduction and Adjustable Door Arm)
- **Auto-Force** Adjustment for Changing Weather and Environmental Conditions
- **Electronic Limits** for Easy Setup
- **Solid State Micro-controller** with Built-In Surge Suppressor (for Replacement Logic Boards, Order Part 050ACTWF)



### DIMENSIONS

| Rail Options     | 7'   | 8'   | 10'   |
|------------------|------|------|-------|
| Installed Length | 124" | 136" | 160"  |
| Max. Opening     | 7'6" | 8'6" | 10'6" |

Headroom Clearance Required: 2"

7"

Per second for door to move upward

### SPEED

7"

Per second for door to move downward

## STANDARD SPECS.

## SECURITY

### SECURITY+ 2.0®

#### RADIO CONTROLS

3-Button Remote Control (893 RGX)

Operating Range: ~200'

Operating Temperature: -30°F to 150°F  
Frequency:

- Remote Control: 310, 315 and 390 MHz Tri-Band
- Garage Door Opener: Frequency Agile on 310, 315, 390 MHz
- Security+ 2.0 Anti-Burglary Coding

### SECURITY +2.0 ENCRYPTED CONTROLS

Multi-Function Control Panel® (882RGDW)

- Program Remote Controls
- Maintenance Alert System
- Easy WiFi Setup

## SMART

### MyQ® RADIO

902-928 MHz

50-Channel FHSS  
(Frequency Hopping Spread Spectrum)

- Provides 2-way communication from garage door opener and MyQ Accessories.
- Enables monitoring and control of garage door openers and lighting controls via smartphone, tablet or computer.

### HOMELINK® COMPATIBLE (VERSION 4.0 OR HIGHER\*)

\*May require an external adapter depending on the model and year of your vehicle. Visit [HomeLink.com](http://HomeLink.com) for additional information.

## ELECTRICAL

### LIGHTING



- Max. 1 100-Watt Light Bulb
- Enhanced CFL (Compact Fluorescent) Compatible, Max. 26 Watts

## SHIPPING.

### SHIPPING WEIGHT (in lbs.)

#### CARTONS (2)

CARTON 1: 20" x 12" x 10"

- Multi-Function Control Panel (882RGDW)
- 3-Button Remote Control (893RGX)
- Garage Door Opener Head (8155WRGD)
- The Protector System® Safety Reversing Sensors

CARTON 2: 10'4" x 5" x 5" (for 7' Rail)

- Assembled Solid-Steel Chain T-Rail



HEAD



RAIL (7')

## CONVENIENCE AND SAFETY.

- Alert-2-Close/Unattended Close Operation†
- Emergency/Quick Release
- Automatic Trolley Reconnect
- Ventilation/Pet Opening
- Down Safety Reverse
- Up Safety Stop
- Safety Beam Obstruction Turns Lights On
- Maintenance Alert System
- Garage Door Opener Capacity of up to 12 Remote Controls, 1 Keyless Entry System and 16 MyQ Devices



HomeLink® and the HomeLink House® logo are registered trademarks of Gentex Corporation

†: To reduce the risk of injury to persons, only use alert-2-Close/Unattended Close Operation features when installed with a sectional door.