

## 1/2 HP AC BELT DRIVE WIFI® GARAGE DOOR OPENER

RELIABLE AND SECURE WITH THE CONVENIENCE OF BUILT-IN WIFI.



WARRANTY

LIFETIME  
Motor and Belt

1-YEAR  
Parts and  
Accessories

RELIABLE



1/2 HP AC MOTOR IS PURPOSEFULLY DESIGNED AND BUILT TO LAST.

BELT DRIVE SYSTEM FOR QUIET, MAINTENANCE-FREE PERFORMANCE.

MOTOR VIBRATION ISOLATION SYSTEM (MVIS®) PROVIDES QUIET, RELIABLE OPERATION.

SMART



FREE MyQ MOBILE APP SO USERS KNOW THEIR HOME IS SECURE.

BUILT-IN WIFI FOR THE EASIEST WAY TO CONNECT THE GARAGE.

REAL-TIME ALERTS INDICATE THE STATUS OF THE GARAGE DOOR VIA EMAIL OR PUSH NOTIFICATIONS.

MONITOR AND CONTROL THE OPENER FROM ANYWHERE USING MOBILE DEVICES.

SECURE

### Security+ 2.0®

SAFEGUARDS GARAGE ACCESS BY SENDING A NEW CODE WITH EVERY CLICK.

POSILOCK® ELECTRONICALLY PROTECTS AGAINST FORCED OPENINGS.

ALERT-2-CLOSE SIGNALS WHEN A DOOR IS BEING CLOSED BY MyQ.

THE PROTECTOR SYSTEM® INVISIBLE LIGHT BEAM AUTO-REVERSES THE DOOR IF THERE IS AN OBSTRUCTION.

### INCLUDED ACCESSORIES:

#### Multi-Function Control Panel®

Turns on garage door opener lights from inside the garage.



6080960

882 RGDW

#### 3-Button Remote Control

Operates up to 3 openers or MyQ Light Accessories.



2220178

893RCX

### PROTECTIVE ADD-ONS:

#### Remote Light Control

Enables home lighting control through a garage remote or a smartphone.



2220174

825LM

#### Garage Door and Gate Monitor

Monitors and closes up to 4 garage doors from any room in the house.



2220175

829LM

#### Mini Universal Remote Control

Compact and portable to provide quick, easy garage access.



2220185

374UT

#### Wireless Keyless Entry

Provides convenient, secure access from outside the garage with a 4-digit PIN.



2220166

877MAX

## MASTERFUL ENGINEERING.

### MOTOR

- ½ Horsepower AC
- 1,625 RPM
- Automatic Thermal Protection

### POWER

- 120V AC
- 60 Hz Voltage
- 6A Current Rating
- UL Listed
- 4' Power Cord (3-Prong)

### MECHANICS

- **Steel Chassis, T-Rail and Trolley**
- **Full Reinforced Belt Drive Mechanism** (16:1 Gear Reduction and Adjustable Door Arm)
- **Auto-Force** Adjustment for Changing Weather and Environmental Conditions
- **Electronic Limits** for Easy Setup
- **AC WiFi Logic Board** with Built-In Surge Suppressor



### DIMENSIONS

Rail Options	7'	8'	10'
Installed Length	128"	140"	164"
Max. Opening	7'6"	8'6"	10'6"

Headroom Clearance Required: 2"

8"

Per second for door to move upward

### SPEED

8"

Per second for door to move downward

## STANDARD SPECS.

## SECURITY

### SECURITY+ 2.0\*

#### RADIO CONTROLS

3-Button Remote Control (893 MAX)

Operating Range: ~200'

Operating Temperature: -30°F to 150°F  
Frequency:

- Remote Control: 310, 315 and 390 MHz Tri-Band
- Garage Door Opener: Frequency Agile on 310, 315, 390 MHz
- Security+ 2.0 Rolling Code Technology

#### SECURITY +2.0 ENCRYPTED CONTROLS

Multi-Function Control Panel\*

- Program Remote Controls
- Maintenance Alert System
- Easy WiFi Setup

## SMART

### MyQ® RADIO

902-928 MHz

50-Channel FHSS

(Frequency Hopping Spread Spectrum)

- Provides 2-way communication from garage door opener and MyQ Accessories.
- Enables monitoring and control of garage door openers and lighting controls via smartphone, tablet or computer.

#### HOMELINK® COMPATIBLE (VERSION 4.0 OR HIGHER\*)

\*May require an external adapter depending on the model and year of your vehicle. Visit [HomeLink.com](http://HomeLink.com) for additional information.

## ELECTRICAL

### LIGHTING



- Max. 2 100-Watt Light bulbs
- Adjustable Time
- Enhanced CFL (Compact Fluorescent) Compatible, Max. 26 Watts

#### ENERGY EFFICIENCY

- Approximately 1.5-Watt Power in Standby mode\*
- \*Occurs at Down Limit When opener's Lights Turn Off

## SHIPPING.

### SHIPPING WEIGHT (in lbs.)

#### CARTONS (2)

CARTON 1: 20" x 12" x 10"

- Multi-Function Control panel
- 3-Button Remote Control
- Garage Door Opener Head
- The Protector System® Safety Reversing Sensors

CARTON 2: 10'4" x 5" x 5"

- Assembled Solid-Steel Belt T-Rail



## CONVENIENCE AND SAFETY.

- Alert-2-Close/Unattended Close Operation†
- Emergency/Quick Release
- Automatic Trolley Reconnect
- Ventilation/Pet Opening
- Down Safety Reverse
- Safety Beam Obstruction Turns Lights On
- Maintenance alert System
- Garage Door Opener Capacity of up to 24 Remote Controls, 2 Wireless Keyless Entry Systems and 16 MyQ Devices



HomeLink® and the HomeLink House® logo are registered trademarks of Gentex Corporation

†: To reduce the risk of injury to persons, only use alert-2-Close/Unattended Close Operation features when installed with a sectional door.